

MULTITONE POWER SPECTRAL DENSITY

CROSS-REFERENCE TO RELATED APPLICATIONS

Priority is claimed from provisional Appl.No. 60/394,358, filed July 8, 2002. The following patent applications disclose related subject matter: Serial Nos. 09/....., filed (-----). These applications have a common assignee with the present application.

BACKGROUND OF THE INVENTION

The invention relates to digital communications, and, more particularly, to discrete multitone communication systems and corresponding circuitry and methods.

Digital subscriber line (DSL) technologies provide potentially large bandwidth (e.g., greater than 20 MHz for subscribers close to the central office) for digital communication over existing telephone subscriber lines (the copper plant). The subscriber lines can provide this bandwidth despite their original design for voice band (0-4 kHz) analog communication. In particular, ADSL (asymmetric DSL) adapts to the characteristics of the subscriber line by using a discrete multitone (DMT) line code with the number of bits per tone (subchannel) adjusted to channel conditions. The bits of a codeword are allocated among the subchannels for modulation to form an ADSL symbol for transmission. Figure 2a illustrates the use of the Fast Fourier transform in a system having, for example, 256 tones with each tone treated as a QAM subchannel (except dc tone 0) and so the kth tone encoding corresponds with a complex number $X(k)$ for $0 \leq k \leq 255$. Extending to 512 tones by conjugate symmetry allows the 512-point IFFT to yield real samples $x(n)$, $0 \leq n \leq 511$, of the transformed block (symbol); and a DAC converts these samples into a segment of the transmitted waveform $x(t)$. Figure 2a also notes a cyclic prefix for each symbol which allows for simplified equalization for the interference of successive symbols which arises from the non-ideal impulse response of the transmission channel.

For example, Annex A of the ADSL standard G.992.3 has subchannels separated by 4.3125 KHz and a band extending up to 1104 KHz for 256 subchannels. Annex A also provides power spectral density (PSD) masks for both central office and customer transmitters plus 0-40 dB power cutback levels to be applied according to

dynamic range measured by the central office and customer receivers during initialization procedures. In higher bandwidth versions of the ADSL standard, the PSD can be shaped for efficient operation, such as limiting crosstalk among physically adjacent subscriber lines and reducing the transmit power requirements. However, power cutbacks for transmitters with shaped power spectral densities (PSDs) can render the low power portions of the spectrum useless.

SUMMARY OF THE INVENTION

The present invention provides a ceiling-based power cutback method for discrete multitone systems.

This has advantages including the improved utilization of the frequency spectrum with power cutback.

BRIEF DESCRIPTION OF THE DRAWINGS

Figure 1 shows preferred embodiment power cutback.

Figures 2a-2b show functional blocks of a discrete multitone system.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

1. Overview

Preferred embodiments provide power cutback methods useful for multitone systems employing transmit power optimization and with shaped power spectral density (PSD) masks. As illustrated in Figure 1, the methods apply a power ceiling (saturation) instead of a uniform power decrease across an entire PSD mask passband. This effectively boosts the relative power of the low power portions of a shaped PSD while still achieving essentially the same total power reduction as a uniform power cutback.

Figures 2a-2b illustrate functional blocks of a discrete multitone system which may use the preferred embodiment methods with PSD and framing part of the encoding prior to IFFT in the transmitter, whereas dynamic range measurements of the received signal occur in the receiver.

Preferred embodiment communications systems use preferred embodiment methods. In preferred embodiment communications systems customer premises transceivers (modems) and central office transceivers (modems) could each include one or more digital signal processors (DSPs) and/or other programmable devices with stored programs for performance of the signal processing of the preferred embodiment methods. Alternatively, specialized circuitry could be used. The transceivers may also contain analog integrated circuits for amplification of inputs and/or outputs and conversion between analog and digital; and these analog and processor circuits may be integrated as a system on a chip (SoC). The stored programs may, for example, be in ROM or flash EEPROM integrated with the processor or external. Exemplary DSP cores could be in the TMS320C6xxx or TMS320C5xxx families from Texas Instruments.

2. Power cutback

Power cutback preferred embodiment methods are ceiling-based and allow for good performance in the high frequency subchannels while achieving the maximum amount of power reduction. Power cutback generally prevents saturation at the receiver for short loops and limits unnecessary interference (crosstalk) to neighboring loops. During initialization the central office and customer transceivers make measurements of

received signal amplitude and/or power which are used to set the automatic gain controls and to signal a power cutback level to the other transmitter. The G.992.3 standard provides for power cutback levels from 0 to 40 dB in 1 dB increments to be applied to the passband; the 6-bit variable PCB encodes the power cutback level. Because systems operating in frequencies above 1104 kHz typically use a shaped PSD, the preferred embodiment power cutback methods should take the shaping into account. In particular, to maximize the power in subchannels with a lower PSD level, the preferred embodiment power cutback methods apply a ceiling on transmit PSD. Thus the power cutback limits the peak of the transmit PSD, by defining a maximum transmit PSD level relative to the peak of the original mask. Hence, subchannels for which the PSD level is less than the peak allowed by the power cutback are unaffected.

More explicitly, the transmitter nominal (template) power level (in terms of dBm/Hz) in each subchannel is defined as the corresponding PSD mask subchannel level minus 3.5 dB (2.5 dB for the maximum fine gain setting plus 1.0 dB for implementation tolerance). Figure 1 illustrates the preferred embodiment power cutback method applied to a nominal PSD (with a peak power level of -40 dBm/Hz) to yield the reference PSD. As shown, the nominal PSD is the 3.5 dB attenuation of the PSD mask; and the power cutback method applies a ceiling of -46 dBm/Hz. Thus the maximal power cutback of 6 dB only occurs for portions of the nominal PSD at a power level -40 dBm/Hz and no power cutback occurs for portions of the nominal PSD at a power level of -46 dBm/Hz or less. Of course, a cutback from -40 dBm/Hz to -46 dBm/Hz is a reduction by a factor of 4.

Using a generalization of G.992.3 notation, the foregoing is expressed as: MAXPSD(f) is a PSD shaped according to the selected mask with the value MAXPSD representing the PSD level at the peak of the mask (which in Figure 1 occurs in the range of subchannels 32-256 or 138-1104 kHz). The PSD level in the range of subchannels 256-512 or 1104-2208 kHz is derived from this peak level. NOMPSD(f) is a PSD shaped according to the selected mask with the value NOMPSD representing the PSD level at the peak of the mask (which in Figure 1 occurs in the range of subchannels 32-256 or 138-1104 kHz). The PSD level in the range of subchannels 256-512 or 1104-2208 kHz is derived from this peak level. Then the reference PSD

level as a function of frequency is $REFPSD(f) = \min\{ NOMPSD(f), NOMPSD - PCB \}$ where PCB is a constant value (e.g., 6 dB in Figure 1). The effect is that PCB imposes a ceiling on the mask. Then as in G.992.3, tss_i (transmitter spectrum shaping) values represent a scaling relative to the $REFPSD(f)$ level, and as such tss_i can be interpreted as putting additional shaping on top of the already-shaped PSD mask. The available PCB levels are 0 dB to 40 dB in 1 dB increments.

3. Modifications

The preferred embodiments may be varied while retaining one or more of the feature of ceiling-based power cutback.

For example, the available cutback range of 0-40 dB and resolution of 1 dB could be varied; the available cutback levels need not be linearly (in terms of logarithms) spaced; the ceiling could be tilted to provide some rolloff with increasing frequency and so forth.